


Specifications Sheet



Motorola Canopy

30 Mbps 5.7 Ghz BH Pair – Integrated



Canopy Part Number	BP5730BH20-2BB
Description	30 Mbps 5.7 Ghz BH Pair – Integrated
Market Availability	North America, Europe, South America, Asia
Signaling Rate	30 Mbps
Typical LOS Range	non-LoS Up to 6 Miles (10Km), near-LoS up to 25 Miles (40Km), LoS Up to 124 Miles (200Km)
Typical Aggregate Useful Throughput	Dynamically variable modulation ranges from 1.5 Mbps to 21 Mbps. (Upgradeable to 60 Mbps via Software License Key)
Frequency range of band	5.725 GHz–5.850 GHz
Channel Width	12 MHz
Modulation Type	Adapting between BPSK and 64QAM – (8 Modes). Signal is transmitted and received with multiple beams on separate routes – re-correlates signals and brings multi-path signals into phase. Generates a new set of Adaptive Modulation margins which reduces the probability of codeword errors (and hence packet loss). TDM mode.
Encryption	Proprietary scrambling, optional AES 128 Bit Encryption
Latency	7ms
Nominal Receiver Sensitivity (dbm typical)	Adaptive, varying between -96.5 dBm and -72 dBm according to modulation selected
Antenna Gain (dB)	System Gain Varies with modulation mode between 168.5 dBm and 138 dBm using integrated antenna
EIRP (dB)	Adaptive. Varying between 25 dBm and -10 dBm according to modulation selected and radio path. Power Source 90-240 VAC, 50-60 Hz/36-60V DC. Power consumption 55W maximum.
Antenna Beam Width	Integrated flat plate / 23 dBi / Narrow 8 degree Beam Width
Temperature	-40°F (-40°C) to +140°F (+60°C) including solar radiation.
Wind Survival	242 km/hr (150 miles/hr)
Dimensions	Indoor Unit: 9.85W x 1.6H x 3.1D inches (250 x 40 x 80 mm)
Weight	Outdoor Unit: 12.1 lbs (5.5 kg) including bracket
Interface	10BASE-T / 100BASE-T (RJ-45) – auto MDI/MDIX switching
Protocols Used	IEEE 802.3 compatible
Network Management	Web Server and SNMP

Specifications subject to change without notice.

MOTOROLA and the Stylized M Logo are registered in the U.S. Patent and Trademark Office. All other product or service names are the property of their respective owners. © Motorola, Inc. 2006